



The Solution for Managing Wireless Users with MikroTik RouterOS

Presented By Mohammad Javad Sabri

MikroTik MUM Dubai October 17, 2016

About me



- Mr. Mohammad Javad Sabri
- Master of Science Computer engineering
- MikroTik Certified Consultant
- MTCNA, MTCWE, MTCTCE, MTCUME
- www.mjsabri.com
- info@mjsabri.com
- **I Love MikroTik**


Table of content

- Applications
- What is HotSpot ?
- What is User Manager ?
- Getting start to Configuration Hotspot
- Configuration in User Manager
- Connect To Wireless network and test Solution

Applications



Hotel




Airport



University

What is HotSpot ?




What is User Manager ?

The screenshot displays the MikroTik User Manager web interface. On the left is a vertical navigation menu with buttons for Routers, Users (highlighted), Sessions, Customers, Logs, Payments, Profiles, Settings, Reports, 0 A sessions, 0 A users, Advanced search, Maintenance, and Logout. The main content area has a top bar with 'Add', 'Edit', and 'Generate' buttons, a search box, and a table header. The table header includes a checkbox, 'Username', 'Till time', 'Total time left', and 'Actual profile'. Below the header, the table is empty. A 'Per page [20]' dropdown is located at the bottom right of the table area.

<input checked="" type="checkbox"/>	Username	Till time	Total time left	Actual profile
.				

Getting start to Configuration Hotspot

DNS



DNS

DNS Settings

Servers: 8.8.8.8

Dynamic Servers:

Allow Remote Requests

Max UDP Packet Size: 4096

Query Server Timeout: 2.000 s

Query Total Timeout: 10.000 s

Cache Size: 2048 KB

Cache Max TTL: 7d 00:00:00

Cache Used: 11

OK


Cancel

Apply


Static

Cache


HotSpot setup




HotSpot setup



HotSpot setup



HotSpot setup



Hotspot Setup


Set HotSpot address for interface

Local Address of Network: 10.5.50.1/24

Masquerade Network

Back Next Cancel

HotSpot setup




Hotspot Setup

Set pool for HotSpot addresses

Address Pool of Network: 10.5.50.2-10.5.50.254

Back Next Cancel

HotSpot setup



HotSpot setup


Hotspot Setup

Select SMTP server

IP Address of SMTP Server: 0.0.0.0

Back Next Cancel

HotSpot setup



HotSpot setup

Hotspot Setup

DNS name of local hotspot server

DNS Name: mikrotik.hotspot

Back Next Cancel

HotSpot setup

Hotspot Setup


Create local HotSpot user

Name of Local HotSpot User: a

Password for the User: a

Back Next Cancel

HotSpot setup



Login page

Please log on to use the internet hotspot service


login

password


HOTSPOT GATEWAY
powered by *MikroTik*

Powered by MikroTik RouterOS

Customize page



Customize page



The screenshot shows a 'File List' window with a toolbar containing icons for file operations and buttons for 'Backup', 'Restore', and 'Upload...'. A search bar labeled 'Find' is also present. The main area is a table listing files and directories. The file 'hotspot/login.html' is selected and highlighted with a red box.

File Name	Type	Size	Creation
auto-before-reset.backup	backup	14.3 KiB	Jul/
hotspot	directory		Jul/
hotspot/login.html	.html file	1293 B	Jul/
hotspot/error.html	.html file	898 B	Jul/
hotspot/errors.txt	.txt file	3615 B	Jul/
hotspot/favicon.ico	.ico file	903 B	Jul/
hotspot/img	directory		Jul/
hotspot/img/logobottom.png	.png file	3925 B	Jul/
hotspot/login.html	.html file	3455 B	Jul/
hotspot/logout.html	.html file	1813 B	Jul/
hotspot/lv	directory		Jul/
hotspot/lv/login.html	.html file	1303 B	Jul/
hotspot/lv/errors.txt	.txt file	3810 B	Jul/

32 items (1 selected) | 8.8 MiB of 16.0 MiB used | 44% free

Connect hotspot to user manager

Connect hotspot to user manager

The screenshot shows the MikroTik WinBox interface. On the left, the 'IP' menu item is highlighted with a red box. In the main menu, the 'Hotspot' option is also highlighted with a red box. The right-hand pane is titled 'Hotspot' and has several tabs: 'Servers', 'Server Profiles', 'Users', 'User Profiles', 'Active', 'Hosts', and 'IP Bindings'. The 'Server Profiles' tab is selected and highlighted with a red box. Below the tabs are three icons: a plus sign, a minus sign, and a funnel. A table displays the list of server profiles:

Name	DNS Name	HTML Directory	Rate Limit (rx/tx)
default		hotspot	
hsprof1	mikrotik.hotspot	hotspot	

The row for 'hsprof1' is highlighted with a red box.

Connect hotspot to user manager

Hotspot Server Profile <hsprof1>

General Login **RADIUS**

Use RADIUS

Default Domain:

Location ID:

Location Name:

MAC Format:

Accounting

Interim Update:

NAS Port Type:

OK
Cancel
Apply
Copy
Remove

Connect hotspot to user manager

The screenshot shows the MikroTik WinBox interface. On the left is a navigation menu with the following items: System, Queues, Files, Log, Radius (highlighted with a red underline), Tools, New Terminal, MetaROUTER, and Partition. The main window displays the 'Radius' configuration page. At the top of this page is a toolbar with several icons: a blue plus sign (+) for adding a new entry, a minus sign (-) for deleting, a checkmark for saving, a crossed-out square for discarding, a document icon for refreshing, a funnel icon for filtering, and a 'Reset Settings' button. The plus sign icon is highlighted with a red rectangular box. Below the toolbar is a table with the following headers: '#', 'Service', and 'Called ID'. The table is currently empty. At the bottom of the table area, there is a status bar that reads '0 items'.

Connect hotspot to user manager

New Radius Server

General Status

Service: ppp login
 hotspot wireless
 dhcp

Called ID:

Domain:

Address: 192.168.1.60

Secret: mikrotik

Authentication Port: 1812

Accounting Port: 1813

Timeout: 300 ms


Accounting Backup

Realm:

Src. Address:

OK
Cancel
Apply
Disable
Comment
Copy
Remove
Reset Status

Connect user manager to hotspot



The screenshot shows the Mikrotik WinBox interface. On the left is a sidebar menu with the following items: System, Queues, Files, Log, Radius (highlighted with a red underline), Tools, New Terminal, MetaROUTER, and Partition. The main window is titled 'Radius' and contains a toolbar with icons for adding (+), deleting (-), checking (✓), unchecking (✗), saving (floppy), and filtering (funnel). There are also buttons for 'Reset Status' and 'Incoming' (highlighted with a red box), and a 'Find' input field. Below the toolbar is a table with the following columns: #, Service, Called ID, Domain, Address, and S. The table is currently empty. At the bottom of the window, it displays '0 items'.

Connect user manager to hotspot

Radius Incoming

Accept

Port: 3799

Requests: 0

Bad Requests: 0

Acks: 0

Naks: 0

OK

Cancel


Apply

Reset Status

Getting start to Configuration User Manager

Login to User Manager

1. First go to this address <http://yourrouteraddress/userman>
2. Login to User Manager With user = admin and without password



The screenshot shows the MikroTik User Manager login interface. At the top, the MikroTik logo is displayed above the text "Mikrotik User Manager". Below this, there are two input fields: "Login" and "Password". The "Login" field is currently empty. Below the input fields is a "Log in" button.

Login to User Manager

The screenshot displays the MikroTik User Manager web interface. On the left is a vertical navigation menu with buttons for Routers, Users (highlighted), Sessions, Customers, Logs, Payments, Profiles, Settings, Reports, 0 A sessions, 0 A users, Advanced search, Maintenance, and Logout. The main content area features a header with 'Add', 'Edit', and 'Generate' options, a search bar, and a table with columns: a checkbox, Username, Till time, Total time left, and Actual profile. The table body is currently empty. A 'Per page [20]' dropdown is located at the bottom right of the table area.

Connect user manager to hotspot

The screenshot displays the MikroTik User Manager web interface. On the left, a navigation menu contains the following items: **Routers**, Users, Sessions, Customers, and Logs. The **Routers** item is highlighted with a blue background and a red border. On the right, a table header is visible with columns for 'Add', 'Edit', and 'Name'. The 'Add' column contains a 'New' button, which is also highlighted with a red border. Below the header, a table row shows a checked checkbox and the text 'Name'.

Connect user manager to hotspot

Router details

▼ Main

Name: R1

Owner: admin

IP address: 192.168.1.40

Shared secret: mikrotik

Time zone: Parent time zone

Disabled:

Log events: Authorization success
 Authorization failure
 Accounting success
 Accounting failure

▲ Radius incoming

CoA support:

CoA port: 3799

Add

Create Profiles and limitations

Create limitations

The screenshot displays the MikroTik User Manager web interface. On the left is a navigation menu with buttons for Routers, Users, Sessions, Customers, Logs, Payments, Profiles, Settings, Reports, and 0 A sessions. The 'Profiles' button is highlighted with a red box. The main content area has two tabs: 'Profiles' and 'Limitations', with the 'Limitations' tab selected and highlighted with a red box. Below the tabs are two buttons: 'Add' and 'Edit', with the 'Add' button highlighted with a red box. Underneath the 'Add' button is a 'New' button, also highlighted with a red box. Below these buttons is a table header with a checkbox and a 'Name' column. The table body is currently empty.

Create limitations

Limitation details

▲ Main

Name: 512Kbps-1GB
Owner: admin

▲ Limits

Download: 0B
Upload: 0B
Transfer: 1G
Uptime:

▲ Rate limits


Rate limit: Rx	256K	Tx	512K
Burst rate: Rx	348k	Tx	768k
Burst threshold: Rx	192k	Tx	384k
Burst time: Rx	16	Tx	16
Min rate: Rx	128K	Tx	256K

Priority: 4

▼ Constraints

Add

Create Profiles



Create Profiles

Create profile

Name: 512Kbps-1GB

Create

Create Profiles

Profiles Limitations

Profile: 512Kbps-1GB

Name: 512Kbps-1GB

Name for users:

Owner: admin

Validity: 30d

Starts: At first logon

Price: 0.00

Shared users: 1

Save profile Remove profile

Unlimited profile

Add new limitation

Create Profiles

Profile part

▼ Period

Days: Sunday
 Monday
 Tuesday
 Wednesday
 Thursday
 Friday
 Saturday

Time: 0:00:00 - 23:59:59

▼ Limits

512Kbps-1GB

New limit Cancel Add

Create Profiles

Profiles Limitations

Profile: 512Kbps-1GB

Name: 512Kbps-1GB

Name for users:

Owner: admin

Validity: 30d

Starts: At first logon

Price: 0.00

Shared users: 1

Save profile Remove profile

Profile limitations

<input type="checkbox"/>	Active	Constraints
<input type="checkbox"/>	Always	Transfer limit: 1024.0 MiB Rate limits: 256K/512K 348K/768K 192K/3

Add new limitation Remove selected limitations

Create Users in User Manager

Create Users

The screenshot displays the MikroTik User Manager web interface. On the left sidebar, the 'Users' menu item is highlighted with a red box. The main content area features a top navigation bar with 'Add', 'Edit', and 'Generate' buttons, where 'Add' is also highlighted in red. Below this, there are two rows of options: 'One' (highlighted in red) and 'Batch'. A dropdown menu is open under 'One', showing 'Username' as the selected option.

Create Users

User details ✕

▲ Main

Username:

Password:

Disabled:

Owner: admin

▼ Constraints

▼ Wireless

▼ Private information

Assign profile:

Create Users

MikroTik
Mikrotik User Manager


Routers
Users
Sessions
Customers
Logs
Payments
Profiles
Settings
Reports
0 A sessions
0 A users
Advanced search
Maintenance
Logout

Add Edit Generate

<input type="checkbox"/>	▼ Username	▼ Till time	▼ Total time left
<input type="checkbox"/>	User1	Not set	

Test Solution

Please Connect to **HotSpot AP2** and Login to Hotspot with **user1** for user and **1234** for password



login

password

HOTSPOT GATEWAY
powered by *MikroTik*

Test Solution

Please go to <http://hotspot2.mikrotik/status> for Check status and log off

Welcome User1!

<u>IP address:</u>	<u>10.5.50.254</u>
<u>bytes up/down:</u>	<u>310.4 KiB / 841.6 KiB</u>
<u>connected:</u>	<u>2m12s</u>
status refresh:	1m

log off

References

1. [http://wiki.mikrotik.com/wiki/Manual:User Manager](http://wiki.mikrotik.com/wiki/Manual:User_Manager)
2. <http://wiki.mikrotik.com/wiki/Manual:IP/Hotspot>
3. [http://wiki.mikrotik.com/wiki/User Manager/Hotspot Example](http://wiki.mikrotik.com/wiki/User_Manager/Hotspot_Example)
4. [http://wiki.mikrotik.com/wiki/Manual:RADIUS Client](http://wiki.mikrotik.com/wiki/Manual:RADIUS_Client)
5. [http://wiki.mikrotik.com/wiki/User Manager/Users](http://wiki.mikrotik.com/wiki/User_Manager/Users)
6. [http://wiki.mikrotik.com/wiki/User Manager/Profiles](http://wiki.mikrotik.com/wiki/User_Manager/Profiles)
7. [http://wiki.mikrotik.com/wiki/Manual:Customizing Hotspot](http://wiki.mikrotik.com/wiki/Manual:Customizing_Hotspot)

Thank You